

# NORAM POWER SYSTEMS.®



Model: **NPS P-100**

## Ratings Range

Standby:	kw	80	100
	kva	100	125
Prime:	kw	72	90
	kva	90	113

Generator:	UCI274D		
Voltage:	120/208-277/480		
Phase:	3		
Hertz:	60		

105° Rise Prime Ratings:  
kw/kva: 100/125    amps: 136



## FEATURES

Perkins RJ51155 Water Cooled Diesel with Engine Safety Shutdowns

Battery with 12 Volt Electric Key Start

Voltage Selector Switch  
120/240V 1-Phase, 120/280 3-Phase, 277/480 3-Phase

Control Panel with Analog Engine and Electrical Gauges

Distribution Panel with 120/240V Single-Phase Outlets with a Full Power 3-Phase Lug Panel

Sound Attenuated Gen-Set Enclosure with Sound Reduction Air-Inlet Baffles, Quiet Type Muffler

Skid Base Design with Built Fuel Tank Mounted within a Fuel Containment Cell (Tank Size for 24 Hours of Operating Run Time)

Skid Base Mounted to a Towable Trailer, Dual-Axle, 3500 lbs. with 15" Tires, Protective Fenders, Dual Safety Chains and DOT Running Lights

Gen-Set Enclosure Powder Coated Off-White (Standard)

Newage Generator - 311 Windings, 12-Wire Class H Insulation

**432.563.9602**

Sales  
FAX 432.561.5622

Production  
FAX 432.563.9606

**9800 W. I-20**  
**Midland, TX 79706**